

OZF5-1

USER MANUAL

HDMI 2.0b Splitter 1x8



HDCP 2.2

Fighting for The Dream

INTRODUCTION

Dear customer

Thank you for purchasing this product. For optimum performance and safety, please read these instructions carefully before connecting, operating or adjusting this product. Please keep this manual for future reference.

Our series of HDMI converters, switchers, extenders, matrixes and splitters are designed to make Your A/V device use more convenient, more comfortable, more productive and more cost-efficient.

The mini 1x8 HDMI 2.0b Splitter use a single HDMI source, accessing to multiple HDMI sinks. The Splitter allows one HDMI device to be split easily to eight HDMI compatible monitors or projectors. The Splitter can also be placed at the end of a long HDMI cable to regenerate the HDMI signal.

Our devices offer solutions for noise, space and security concerns, data center control, information distribution, conference room presentation, school and corporate training environments.

FEATURES

- One HDMI input signal split to eight HDMI sink devices
- Support 3D. 3840X2160/60HZ.
- Support deep color 30bit, 36bit
- Support Blue-Ray 24/50/60fs/HD-DVD/xvYCC
- Digital audio format, as DTS-HD/Dolby-trueHD/LPCM7.1/DTS/Dolby-AC3/DSD
- Support signal retiming
- Support input up to 10metres AWG26 HDMI standard cable length, output up to 15metres AWG26 cable length
- No loss of quality
- Installs in minutes
- Need DC5V/2A power supply

The accessories with the machines lists as picture:

- 1、5V Power Adaptor
- 2、one pc of Manual

Operating and Connecting:

- 1、Connect one cable from HDMI source devices into HDMI 2.0b Splitter input.
- 2、Connect one cable from each display (monitor or projector) into the HDMI 2.0b Splitter outputs.
- 3、Connect 5V power supply to the HDMI 2.0b 1x8 Splitter.

SPECIFICATIONS:

HDMI versionHDMI 2.0b
HDMI resolutionup to 3840*2160/60Hz (RGB 4:4:4)
Support video color format24bit/deep color 30bit,36bit
Support audio formatDTS-HD/Dolby-trueHD/LPCM7.1/DTS/Dolby-AC3/DSD
Max bandwidth600MHz
Max baud rate18.5 Gbps
Input/Output TMDS signal 0.5~1.5Volts p-p(TTL)
Input/Output DDC signal5Volts p-p(TTL)
Input cable distance≤10m AWG26 HDMI standard cable
Output cable distance≤15m AWG26 HDMI standard cable
Max working current2A
Power adapter format..Input:AC (50HZ, 60HZ) :100V-240V; Output: DC5V/2A
Operating Temperature range (-15 to +55℃)
Operating Humidity range5 to 90%RH (No Condensation)
Dimension (L x W x H)230x88x25 (mm)
Weight405g

Notes:

Pls use the machine as the instruction listed to keep the long use lifetime of the machine.

- 1.The machine should be placed at the spot far from the Damp, High-Temperature, Dusty, Erosive, and oxidative environment.
- 2.All parts will be free from the strong shake, hit, fall.
- 3.Touching the power adaptor with the wet hands is prohibited.
- 4.Pls hold the power adaptor head and do not pull the power cord when cut off from the socket.
- 5.Pls turn the power off when the machines not used for long time.
- 6.Pls do not open the cover and do not touch the inside parts.
- 7.Pls use the original factory power adaptor.
8. If the screen appear red, it is caused by the display does not support Dolby vision. we recommend to turn off the Dolby vision of the input source.

Before power on, pls check the connection line carefully. And make sure that all interfaces are normally connected. The common trouble shooting way shows below:

Serial NO	Trouble Description	Cause and Ways to deal with
1	Non-Power-Connected	1、 Check if the power adaptor head is truly and correctly inserted the power socket, 2、 Check the power switch if it is in on status.
2	No Picture	1、 Pls to make sure that the TV is on and has been connected with the machine. 2、 To check if the signal source is on and well connected. 3、 Check the system connection quality. 4、 Check if the line is all good quality. 5、 Check the cable quality
3	Obscure Picture	1、 To try again to connect the cable to be free from the unsuccessful connection. 2、 HDMI Cable Quality