

Data sheet of VF-TROLLEY-36



36-Port USB Type-A+C Charging & PDU Charging Trolley

SPECIFICATION

	725mm Width x435mm Depthx760mm Height
Features	<p>Provides the storage space and the charging requirement with the 36-port Type-A+C sockets, and 36-port Shuko sockets, up to 14-inch device</p> <ol style="list-style-type: none"> 1). Front acrylic glass door. It has good transparency, and beautiful vision; 2). It use combination lock, and will be much safe; 3). When open the door, light will automatically open; 4). Front door can be with over 180 turning degree; 5). 4 silent brake casters at the bottom, with rubber anti-collision around the bottom; 6). PDU with current and Amp function. Show contents as below: <ol style="list-style-type: none"> a.) Power interface: display content "W" and metering alarm when the power value exceeds the set power; b.) Current interface: Display content "A" and current value;

	<p>c.) Voltage interface: display content V and voltage value;</p> <p>d.) Current electricity usage interface: The display content "KWH" and the electricity consumption value can be reset to zero. Explanation: Electricity consumption is commonly known as degree, and the electricity consumption power of the electrical appliance (in KW) * time (in H);</p> <p>e.) Frequency interface: display content "frequency" and frequency values;</p> <p>f.) Electricity fee interface: display content "Electricity fee" and electricity fee value;</p> <p>g.) Power factor interface: display content "factor" and factor value</p> <p>7). Safe electricity and protection of equipment. The external indicator light switch controls the fan and LED light. While the internal circuit breaker controls USB sockets and Shuko sockets;</p> <p>8.) Fan unit with temperature control. When reach 37°C, it'll start to working.</p>
Input	AC 100V~240V, 50/60Hz; Max current 16A
Power sockets	36-port Type-A+C sockets, and 36-port Shuko sockets



